


Lesson 06: How to make an "S" hook



Materials:
Wire

Tools:
Wire cutters
Round nose pliers
File or wire-rounder tool


- 1 Cut a piece of wire 3.20cm in length. Smooth the ends of the wire using a file or a wire-rounded tool. Using a marker mark the centre of the wire.




- 2 Bend the wire halfway from the centre placing it in the larger part of the round nose pliers and make a U shape.



- 3 Repeat step 2 for the other end of the wire but now bending it in the opposite direction.



- 4 Align the ends of the wire to the centre and curl them



- 5 Gently mould the wire in a "S" shape.★



Designer's Tip!

You could use the "S" hook to finish necklaces, bracelets or as a component as part of your design.

